

L-Band Distributing Matrix 16²



The final product may vary from the above image depending on the options selected.

Product:

DEV 1985/16x16	16x16 Distributing Matrix 16 ² ; 850...2450 MHz; 75 Ohm, F (f)
DEV 1985/16x8	16x8 Distributing Matrix 16 ² ; 850...2450 MHz; 75 Ohm, F (f)

Features:

- Up to 16x20 in 2 RU
- Various Input and Output Modules
 - 75 Ohm, F (f) or BNC (f), or 50 Ohm, SMA (f)
 - Optical Inputs
- Variable Gain (MGC or AGC)
- Variable Slope
- RF Sensing
- LNB Powering per 4 Input Channels, switchable 13/18 V and 22 kHz Tone
- Graphical Local User Interface
- Integrated Spectrum Analyzer
- Input Channel Redundancy
- Power Supply Redundancy
- Secure Lock Operation
- SNMP Support
- Easy to use DEV Web Interface
- Signal Recording and Data Backup Feature

Technical Data

DEV 1985 Distributing Matrix 16²

Capacity

Number of Inputs x Outputs	DEV 1985/16x16:	16x16 (up to 16x20)
	DEV 1985/16x8:	16x8

RF Specifications

Frequency Range	850...2450 MHz
Impedance, Connectors	75 Ohm, precision F (f)
Damage Level	+25 dBm
Operational Input Level	<-5 dBm
Input Level	-70...-5 dBm
OP1dB	max. 0 dBm
Return Loss	>14 dB
Variable Gain	30 dB
Flatness	±4.0 dB (over entire Band) ±1.0 dB (in any 36 MHz Interval)
Isolation	Input/Input, Output/Output: typ. 60 dB Input/Output (Crosstalk): typ. 60 dB Off: typ. 80 dB
Intermodulation Distortion	<-40 dBc (two Tones @ -8 dBm)
Group Delay Distortion	<7 ns
Noise Figure	<17dB @ -40dBm Input Level
Relay Type	Semiconductor
Switching Delay	<1 s (between Reception and Execution of Command)
Switching Repetition Rate	min. 5 s

Local Operation

Display	2.2" Full Color (18 Bits)
Controls	Rotary Switch

Remote Communication

Interface (Connector)	Ethernet (RJ-45)
Remote Control & Surveillance (Interface)	<ul style="list-style-type: none"> • via Web Interface (Ethernet) • via SNMP (Ethernet)

Redundant Power Supply

Supply Voltage	100...240 V AC supplied by two different Lines
Power Consumption	< 150 VA

General Specifications

Size	19" (483 mm) Width, 2 RU (89 mm) Height, ~300 mm Depth
Weight	~10 kg
Environmental Conditions	ETS 300019 Part 1-3 Class 3.1E

Technical Data (cont.)

- Option 20I** **Change 4 Input Channels to 50 Ohm, SMA (f)**
Option 20B **Change 4 Input Channels to 50 Ohm, SMA (f) with LNB Powering**
Option 20O **Change 4 Output Channels to 50 Ohm, SMA (f)**

Per Option 20I (20O), one input (output) module with four channels is equipped with 50 Ohm, SMA (f) connectors instead of 75 Ohm, F (f) connectors.

With Option 20B the four channels of one input module are capable to deliver LNB power in addition:

LNB Power & Current Monitoring

LNB Power max. 350 mA per Input
Voltage and Tone Control 13 V, 18 V and 0 Hz, 22 kHz

Adjustable Level Setting:

- Upper Alarm Level • max. 330 mA
- Lower Alarm Level • min. 50 mA

- Option 21I** **Change 4 Input Channels to 75 Ohm, BNC (f)**
Option 21B **Change 4 Input Channels to 75 Ohm, BNC (f) with LNB Powering**
Option 21O **Change 4 Output Channels to 75 Ohm, BNC (f)**

Per Option 21I (21O), one input (output) module with four channels is equipped with 75 Ohm, BNC (f) connectors instead of 75 Ohm, F (f) connectors.

With Option 21B the four channels of one input module are to deliver LNB power, in addition:

LNB Power & Current Monitoring

LNB Power max. 350 mA per Input
Voltage and Tone Control 13 V, 18 V and 0 Hz, 22 kHz

Adjustable Level Setting:

- Upper Alarm Level • max. 330 mA
- Lower Alarm Level • min. 50 mA

- Option 22I** **Change 4 Input Channels to Optical providing LC/APC**

Per Option 22I, one input module with four channels is equipped with LC/APC optical connectors instead of 75 Ohm, F (f) RF connectors.

Optical Specifications

Fiber Type Single Mode 9/125 μm
Connector Type LC/APC
Wavelength 1100...1650 nm
Min. optical Input Level
(optical Sensitivity) -22 dBm
Damage optical Input Level +10 dBm

- Option 23B** **Change 4 Input Channels to 75 Ohm, F (f) with LNB Powering**

Per Option 23B, the four channels of one input module with 75 Ohm, F (f) connectors are capable to deliver LNB power:

LNB Power & Current Monitoring

LNB Power max. 350 mA per Input
Voltage and Tone Control 13 V, 18 V and 0 Hz, 22 kHz

Adjustable Level Setting:

- Upper Alarm Level • max. 330 mA
- Lower Alarm Level • min. 50 mA

- Option 25** **Variable Slope (all Channels)**

With Option 25, the device provides slope control for all paths.

Variable Slope 0...5 dB

Technical Data (cont.)

Option 36 **Integrated Spectrum Analyzer**

With Option 36, the matrix is delivered with integrated spectrum analyzer functionality to be operated via Web Interface. The matrix chassis provides a dedicated external 50 Ohm, SMA (f) spectrum analyzer input port for connecting any signal to be probed.

For the technical data of the spectrum analyzer, please refer to the separate spec sheet.

Option 38 **Secure Lock Operation**

With Option 38, the matrix provides the ability of Secure Lock Operation for multiple user operation. While each user can be configured to operate dedicated inputs and outputs, Secure Lock Operation allows user X to lock a switched path while user Y cannot unlock this path to prevent unwanted service interruptions. Admin user is able to overwrite any path locked by normal users.

Option 48 **Input Channel Redundancy**

With Option 48, the matrix software provides the ability to configure redundant input channel configurations. Triggered via the integrated RF Sensing functionality an assigned redundancy channel can take over autonomously the signal transport of a main channel. The switching back to the main channel can be performed either manually or automatically.

Option 85 **4 Input Channels less**

Option 86 **4 Output Channels less**

With Option 85 or Option 86, the device is delivered with four input channels or with four output channels less. Thus, the standard configuration can be equipped with less input or output channels. This provides the flexibility to configure the device for the current requirements and to keep the option to upgrade the device to an application specific maximum size. The field upgrade can be performed by the customer by ordering the appropriate input module or output module.

Order Information

Products

DEV 1985/16x16	16x16 Distributing Matrix 16 ² ; 850...2450 MHz; 75 Ohm, F (f)
DEV 1985/16x8	16x8 Distributing Matrix 16 ² ; 850...2450 MHz; 75 Ohm, F (f)

Options

Option 20I	Change 4 Input Channels to 50 Ohm, SMA (f)
Option 20B	Change 4 Input Channels to 50 Ohm, SMA (f) with LNB Powering
Option 20O	Change 4 Output Channels to 50 Ohm, SMA (f)
Option 21I	Change 4 Input Channels to 75 Ohm, BNC (f)
Option 21B	Change 4 Input Channels to 75 Ohm, BNC (f) with LNB Powering
Option 21O	Change 4 Output Channels to 75 Ohm, BNC (f)
Option 22I	Change 4 Input Channels to Optical providing LC/APC
Option 23B	Change 4 Input Channels to 75 Ohm, F (f) with LNB Powering
Option 25	Variable Slope (all Channels)
Option 36	Integrated Spectrum Analyzer
Option 38	Secure Lock Operation
Option 48	Input Channel Redundancy
Option 85	4 Input Channels less
Option 86	4 Output Channels less

Modules

(Input Modules and Output Modules for Upgrade or as Spare Part)

DEV 13-0347	Input Module, 4 Paths; 850...2450 MHz; 75 Ohm, F (f)
DEV 13-0348	Input Module incl. LNB Powering, 4 Paths; 850...2450 MHz; 75 Ohm, F (f)
DEV 13-0349	Output Module, 4 Paths; 850...2450 MHz; 75 Ohm, F (f)
DEV 13-0350	Input Module, 4 Paths; 850...2450 MHz; 75 Ohm, BNC (f)
DEV 13-0351	Input Module incl. LNB Powering, 4 Paths; 850...2450 MHz; 75 Ohm, BNC (f)
DEV 13-0352	Output Module, 4 Paths; 850...2450 MHz; 75 Ohm, BNC (f)
DEV 13-0353	Input Module, 4 Paths; 850...2450 MHz; 50 Ohm, SMA (f)
DEV 13-0354	Input Module incl. LNB Powering, 4 Paths; 850...2450 MHz; 50 Ohm, SMA (f)
DEV 13-0355	Output Module, 4 Paths; 850...2450 MHz; 50 Ohm, SMA (f)
DEV 13-0253	Optical Input Module, 4 Paths; LC/APC

Order Example

16x20 Distributing Matrix 16²; 850...2450 MHz; 75 Ohm, F (f) with LNB Powering for all Input Channels

- 1* DEV 1985/16x16
- 4* Option 23B
- 1 * DEV 13-0349

Contact

DEV Systemtechnik GmbH
 Grüner Weg 4A
 61169 Friedberg
 GERMANY
 Phone: +49 6031 6975 100
 Fax: +49 6031 6975 114
 info@dev-systemtechnik.com
 www.dev-systemtechnik.com

Rev. 23-Aug-2018

Technical specifications are subject to change