

FRC0710 UPCONVERTER FRC0720 DOWNCONVERTER FRC0730 UP AND DOWNCONVERTER



The FRC0730 is a high performance synthesized up- and downconverter designed for a wide range of broadcast, telco and IP satellite applications. In its default configuration, the FRC0730 upconverts IF signals (70 or 140 MHz) to L-band (950–2150 MHz) and simultaneously downconverts L-band signals (950–2150 MHz) to IF. Optionally, the FRC0730 can upconvert IF signals to C, Ku or DBS-band.

The FRC0730 offers some advanced and unique features such as a calibrated high linearity over the entire bandwidth combined with a very high frequency stability. These features make the FRC0730 the perfect solution for a wide range of transmissions ranging from very small carriers to full transponder applications. The IF frequency is switchable from 70 MHz to 140 MHz and the L-band frequency is adjustable in steps of 48 Hz.

The high output frequency stability is provided by an internal 10 MHz reference clock. For applications requiring a very high frequency stability, such as very low data rate carriers, an optional 0.01 ppm stability reference clock can be ordered separately.

A switchable DC power supply and a reference frequency on the L-band output are also available as options, providing a compact and cost effective solution when the FRC0730 is used in combination with an outdoor RF Upconverter and/or amplifier.

Optionally, an LNB power supply, a frequency band selection signal and a 10 MHz reference frequency can be delivered to an LNB via the L-band input.

The FRC07x0 are easy to operate and monitor. All control and monitoring parameters are available locally on the front panel and remotely through a web interface. It is also possible to control or monitor the FRC07x0 via RMCP or SNMP.

The FRC0730 is also available as a stand-alone upconverter (model number FRC0710) or as a stand-alone downconverter (model number FRC0720).

Key Features

- Agile IF to extended L-band up- and downconverter
- Optional up-conversion to C, Ku or DBS-band
- Ultra fine frequency resolution
- IF frequency switchable between 70 MHz & 140 MHz
- Switchable spectrum inversion
- Excellent flatness over 40/80 MHz bandwidth
- Very high frequency stability
- Very low spurious characteristics
- Phase noise compliant to Intelsat IBS/ Eutelsat SMS
- Phase noise @ L-band compliant to Intelsat IESS-316
- High linearity over the entire bandwidth
- Optional 10 MHz + DC power for BUC
- Optional LNB power supply + 10 MHz

Applications

- Earth Stations
- Broadcast Direct-to-home (DTH) uplinks
- Digital Satellite News Gathering (DSNG)
- Telco and trunking satellite infrastructures
- VSAT hubs
- Generic satcom applications

Related Products

- [FRC0740](#) L-Band Block UpConverter
- [FRC0750](#) Active L-Band Combiner and Upconverter
- [USS0202](#) Universal Redundancy Switch

Interfaces

Upconverter

Input Interface (IF):

Connector	BNC (F), 75 Ohm optional (FRC0710)
Return loss	19 dB minimum (70 \pm 20 MHz)
	17 dB minimum (140 \pm 40 MHz)
	20 dB minimum (70 Ohm)
Frequency range	70 MHz +/- 20 MHz
	140 MHz +/- 40 MHz (selectable)
Input level IF (typical)	-35 to +5 dBm
Input level IF (non-damage)	+15 dBm maximum

Output Interface (L-band):

Connector	SMA (F), 50 Ohm N(F), 50 Ohm with option (FA-09 and FA-10)
Return loss	>15 dB
Frequency range	950-2150 MHz
Frequency step size	48 Hz
Output level	-30 to +10 dBm

Output Interface (RF)(Optional):

Connector RF-band out	SMA (F), 50 Ohm
Return loss	18 dB minimum (C- and Ku-band)
	12 dB minimum (DBS-band)
Output level (P1 dB)	+13 dBm minimum (C-band)
	+15 dBm minimum (Ku-band)
	+10 dBm minimum (DBS-band)
Spectrum inversion	Selectable
Frequency range RF-band	
C-band	5.85 – 7.05 GHz
Ku-band	12.75 – 13.25 GHz
Ku-band	13.75 – 14.80 GHz
DBS-band	17.30 – 18.10 GHz
DBS-band	17.60 – 18.4 GHz
LO leakage	-72 dBm maximum (C-band)
	-75 dBm maximum (Ku- and DBS-band)

BUC Power and Reference Frequency (Optional):

Max. current	3 Amps
Voltage	24V, 48V
Frequency	10 MHz
Stability	$\pm 5 \times 10^{-8}$ over 0°C to 65°C

Channel Characteristics

Gain:

Programmable IF gain	-15 to 20 dB
Programmable L-band gain	-20 to +20 dB
Programmable L-band+RF gain	-10 to +30 dB
Gain step size	0.1dB
Amplitude response over 40/80 MHz BW (L-band)	0.5 dB peak-to-peak
Amplitude response over 40/80 MHz BW (RF)	0.7 dB/40 MHz 1.5 dB/80 MHz 2.0 dB/80 MHz (14.5 - 14.8 GHz)
Level stability (typ.)	± 1.0 dB over 0 to 50°C ± 0.5 dB over 20 to 40°C
Gain slope (over 10 MHz minimum)	0.03 dB/MHz maximum

Linearity:

Output 1dB compression (L-band)	>+10 dBm
Output 1dB compression (RF)	>+10 dBm
Third order intermod @ 0 dBm output	<-54 dBc (C-band) <-50 dBc (Ku- and DBS-band)
Third order intercept (L-band)	>+26 dBm
Third order interception (RF-band)	>+20 dBm
AM/PM conversion	0.1°/dB maximum @ 0 dBm out

Switching:

Output switching suppression	<-80 dBm
------------------------------	----------

Noise & Spurious:

Noise figure at minimum attenuation	15 dB maximum
Noise power density	-129 dBm/Hz maximum
Spurious outputs	
Signal related (in-band)	-65 dBc up to 0 dBm output
Signal independent	-80 dBm maximum (C-band) -72 dBm max. (Ku- & DBS-band)

Phase noise

	L-band	C-band/Ku-band/ DBS-band	External refer- ence
@ 10 Hz	<-50 dBc/Hz	<-35/50/50 dBc/Hz	-120 dBc/Hz
@ 100 Hz	<-72 dBc/Hz	<-70/72/60 dBc/Hz	-150 dBc/Hz
@ 1KHz	<-81 dBc/Hz	<-80/86/75 dBc/Hz	-160 dBc/Hz
@ 10 KHz	<-90 dBc/Hz	<-90/99/85 dBc/Hz	-160 dBc/Hz
@ 100 KHz	<-95 dBc/Hz	<-100/102/95 dBc/Hz	-160 dBc/Hz

Group Delay:

	@ 80 MHz BW	@ 40 MHz BW
Linear group delay (max.)	0.02 ns/MHz	0.03 ns/MHz
Parabolic group delay (max.)	0.0004 ns/MHz ²	0.004 ns/MHz ²

For more information please contact your Sales Representative at sales@idirect.net.