

32 Port Fan-Out Dual Band RF Matrix Switch

QX12200V8X24CS2AA1000

8x24 SMA 50 Ω (f)

Exclusive Flexible Matrix Architecture, Industry Leading Specifications, and Hot-Swappable Components Provide an *XTREME* Signal Management Solution

The XTREME 32 Dual Band matrix switch is a full fan-out (distributive) non-blocking signal management solutior that routes an input to any or all outputs. The design features an industry exclusive architecture that supports both symmetric and asymmetric configurations of 32 combined inputs and outputs in a compact 1 RU chassis Hot-Swappable redundant power supplies, I/O Modules, and a field replaceable cooling fan provide maximum reliability.

50-200 MHz & 850-2500 MHz Operating RangeHot-swappable Input and Output AdaptersFlexible Matrix Configurations (16x16, 4x28, 8x24)Adjustable Input and Output GainOptional LNB Power 13/18 V with 22 kHz ToneRedundant HotDual Gigabit Ethernet PortsSwappable Power SuppliesField Replaceable Cooling Fan







Esatcom Inc.

www.esatcom.com

Tel: 718.799.0084 Email: sales@esatcom.com



32 Port Fan-Out Dual Band RF Matrix Switch

Specifications and Operating Conditions

As Configured/Expandable to:	8x24			
RF Connectors:	SMA 50 Ω (f)			
Operating Frequency:	50-200 MHz & 850-2500 MHz			
Operating Frequency.	50-200 MHz	:	950-2150 MH	z 850-2500 MHz
Frequency Response: Default Gain: typically Centered @ 0 dB	+/- 2.5 dB		+/- 1.5 dB	+/- 2.5 dB
Any 36 MHz:	+/8 dB		+/5 dB	+/7 dB
Input P1dB:				
Default Gain:	0 dBm min			
Max Input Gain:	-10 dBm typical *			
Noise Figure:				
Default Gain:	20 dB max		13 dB max	14 dB max
Max Input Gain:	10 dB typical	*	9 dB typical *	10 dB typical *
OIP3:				
Default Gain:	9 dBm min		10 dBm min	9 dBm min
Input Return Loss:	12 dB min		14 dB min	12 dB min
Output Return Loss:	12 dB min		14 dB min	12 dB min
Isolation:				
Input to Input:	60 dB min			
Output to Output:	60 dB min			
Input to Output:	55 dB min		50 dB min	50 dB min
Input Gain Range:	-2	23.5	5 to 8 dB in .5 dl	3 steps
Output Gain Range:	-15.5 to 16 dB in .5 dB steps			
RF Sensing Range:		-50 to 0 dBm		
AGC Tracking Range:		-50) to -10 dBm set	point
Switching Speed:	150 mS per crosspoint typical *			
	<	:2 u	IS from break to	make
Maximum Input Power: (No Damage)	20 dBm (30 VDC max on any port)			

Control:				
Local Control:				
Front Panel 2.2" LCD Display with Rotary Knob				
Remote Control:				
Dual 10/100/1000 Base Tx Ethernet Ports				
v2c, v3				
Quintech 2.15 Protocol (Port 9100)				
Web Server				
Secure Web Server with Custom SSL Certificate				
TELNET with option to disable				
Macro Scripting Language to Automate Changes and Monitoring				
XR Bus Expansion Standard				
Optional Ethernet Expansion				
NTP Time Client				

Alarms and Logging:		
SNMP Traps on Status Change		
SNMP Trap on Crosspoint Change		
SysLog, SQL, or CSV Format Log File		
Q-Sense:		
Primary and Backup Input Pairs: Backup is automatically switched if the Primary Input falls below the threshold level.		

Power and Cooling Requirements:		
AC Input Range:	100-240 VAC Autoranging 50/60 Hz 5A max	
Hot-Swappable Redundant Supplies with Separate AC Inlets		
Power Consumption:	100 W typical, 350 W with LNB option	
Fan:	Long-life ball bearing fan (field swappable)	
Input and Output RF Modules:	Hot Swappable	

Physical:		
Dimensions:	1 RU (1.75" H x 19" W x 18.5" D)	
Weight:	14 lbs.gross (boxed), 11.2 lbs. net	
Certifications:	CE, TUV NRTL, FCC Part 15	

Environmental Parameters:		
Operating Temperature:	0 to 50° C	
Storage Temperature:	-10° C to 75°C	
Humidity:	20 % to 90% non-condensing	
Altitude:	10,000 feet AMSL	

* typical refers to expected product performance that is useful in application of the product but is not covered by the product warranty



Esatcom Inc. www.esatcom.com

Tel:	Email:
718.799.0084	sales@esatcom.com