

XTREME 32

32 Port Fan-Out Dual Band RF Matrix Switch

QX12200V16X16CS4AA1001

16x16 SMA(f) LNB Power

Exclusive Flexible Matrix Architecture, Industry Leading Specifications, and Hot-Swappable Components Provide an XTREME Signal Management Solution

The XTREME 32 Dual Band matrix switch is a full fan-out (distributive) non-blocking signal management solution that routes an input to any or all outputs. The design features an industry exclusive architecture that supports both symmetric and asymmetric configurations of 32 combined inputs and outputs in a compact 1 RU chassis. Hot-Swappable redundant power supplies, I/O Modules, and a field replaceable cooling fan provide maximum reliability.

850-2500 MHz Operating Range

Flexible Matrix Configurations (16x16, 4x28, 8x24)

LNB Power 13/18 V with 22 kHz Tone

Redundant Hot Swappable Power Supplies

Hot-swappable Input and Output Adapters

Adjustable Input and Output Gain

Dual Gigabit Ethernet Ports

Field Replaceable Cooling Fan



Convenient Local Control and Status Monitoring

Field Replaceable Cooling Fan

Hot Swappable I/O Adapters

Independent Input and Output gain control to balance levels and cable loss

Dual Gigabit Ethernet Ports Remotely controllable via secure web browser interface, SNMP, TCP, API, or TELNET



SMA, BNC 50, BNC 75, and mixed connector configurations available.

Hot-swap Redundant Power Supplies



Esatcom Inc.
www.esatcom.com

Tel:
718.799.0084

Email:
sales@esatcom.com

XTREME 32

32 Port Fan-Out Dual Band RF Matrix Switch

Specifications and Operating Conditions

As Configured/Expandable to:	16x16	
RF Connectors:	SMA(f)	
Operating Frequency:	850-2500 MHz	
	950-2150 MHz	850-2500 MHz
Frequency Response: Default Gain: typically Centered @ 0 dB	+/- 1.5 dB	+/- 2.5 dB
	Any 36 MHz:	
	+/- .5 dB	+/- .7 dB
Input P1dB:	0 dBm min	
	Default Gain:	
	-10 dBm typical *	
Noise Figure:	13 dB max	14 dB max
	Default Gain:	
	9 dB typical *	10 dB typical *
OIP3:	10 dBm min	
	9 dBm min	
Input Return Loss:	14 dB min	12 dB min
Output Return Loss:	14 dB min	12 dB min
Isolation:	60 dB min	
	Input to Input:	
	60 dB min	
Output to Output:		
Input to Output:	50 dB min	50 dB min
Input Gain Range:	-19.5 to 12 dB in .5 dB steps	
Output Gain Range:	-15.5 to 16 dB in .5 dB steps	
RF Sensing Range:	-50 to 0 dBm	
AGC Tracking Range:	-50 to -10 dBm setpoint	
Switching Speed:	150 mS per crosspoint typical *	
	<2 uS from break to make	
Maximum Input Power: (No Damage)	20 dBm (30 VDC max on any port)	
LNB Power: Each Port	0/13/18 V, 22 kHz	
	250 W available, Individual ports limited to 750 mA	
	Short Circuit Protection with Automatic Reset	
	Status: Under Current (<50 mA), Short, and Normal	

* typical refers to expected product performance that is useful in application of the product but is not covered by the product warranty

Control:	
Local Control:	
Front Panel 2.2" LCD Display with Rotary Knob	
Remote Control:	
Dual 10/100/1000 Base Tx Ethernet Ports	
SNMP	v2c, v3
TCP/IP	Quintech 2.15 Protocol (Port 9100)
Web Server	
Secure Web Server with Custom SSL Certificate	
TELNET with option to disable	
Macro Scripting Language to Automate Changes and Monitoring	
XR Bus Expansion Standard	
Optional Ethernet Expansion	
NTP Time Client	

Alarms and Logging:	
SNMP Traps on Status Change	
SNMP Trap on Crosspoint Change	
SysLog, SQL, or CSV Format Log File	
Q-Sense:	
Primary and Backup Input Pairs: Backup is automatically switched if the Primary Input falls below the threshold level.	

Power and Cooling Requirements:	
AC Input Range:	100-240 VAC Autoranging 50/60 Hz 5A
Hot-Swappable Redundant Supplies with Separate AC Inlets	
Power Consumption:	100 W typical, 350 W with LNB option
Fan:	Long-life ball bearing fan (field swappable)
Input and Output RF Modules:	Hot Swappable

Physical:	
Dimensions:	1 RU (1.75" H x 19" W x 18.5" D)
Weight:	14 lbs. gross (boxed), 11.2 lbs. net
Certifications:	CE, TUV NRTL, FCC Part 15

Environmental Parameters:	
Operating Temperature:	0 to 50° C
Storage Temperature:	-10° C to 75° C
Humidity:	20 % to 90% non-condensing
Altitude:	10,000 feet AMSL