

Smart Intelligent Optribution® Chassis 4 RU



The final product may vary from the above image depending on the options selected.

Product:

DEV 7134

Smart Intelligent Optribution® Chassis; 12 Slots

Features:

- ▀ Versatile 4 RU Chassis with small Installation Depth
- ▀ All Modules and Components are assembled at the Front Side
- ▀ 50 Ohm, SMA (f) or 75 Ohm, F (f)
- ▀ 1+1 Redundancy Options
- ▀ Automatic Switch Back Option for 1+1 Redundancy Options
- ▀ N+1 Redundancy Options
- ▀ RGC (Redundancy Path Gain Compensation) for N+1 Redundancy Options
- ▀ CWDM for 4, 8, and 9 Channels
- ▀ Optical Ethernet Options
- ▀ SNMP Support
- ▀ DEV Web Interface
- ▀ Signal Recording and Data Backup Feature
- ▀ Power Line and Power Supply Redundancy

DEV 7134 Smart Intelligent Optribution® Chassis; 12 Slots

	Value	Condition
Capacity		
Front Side	12 Slots (max. 12 Optical Channels with Single Link Modules, max. 16 Optical Channels with Twin Modules)	
Remote Communication		
Interface (Connector)	Ethernet (RJ-45)	
Remote Control & Surveillance	via Web Interface and via SNMP	
Redundant Power Supply		
Supply Voltage	100...240 V AC supplied by two different Lines	
Power Consumption	<100 VA	
General Specifications		
Size	19" (483 mm) Width, 4 RU (178 mm) Height, ~255 mm + max. 80 mm (Optical Connectors) Depth	
Weight	~8 kg	empty Chassis
Environmental Conditions	ETS 300019 Part 1-3 Class 3.1	

Option 28 Automatic Switch Back

Automatic Switch Back enables the autonomous switching back from the redundant link to the main link based on the RF Sensing functionality.

■ Available in combination with 1+1 Rx redundancy options, only

Option 55 Change Ethernet to optical Ethernet Interface; 30 km

Option 56 Change Ethernet to optical Ethernet Interface; 1530 nm; 100 km

Option 57 Change Ethernet to optical Ethernet Interface; 1550 nm; 100 km

With Option 55, Option 56, or Option 57 the CPU module of the device provides a 100Base-FX Ethernet interface with SC/PC connectors (instead of the standard 100Base-TX Ethernet interface with RJ-45 connector) for the optical transmission of Ethernet signals.

Cabling Options

Cabling options are used for stand-alone optical Tx or Rx modules.

■ Available in 50 Ohm with SMA (f) or in 75 Ohm with F (f) connectors

■ Available for DC...3000 MHz, or for 10...1006 MHz, or for DC, 700...2300 MHz

1+1 Redundancy Options

1+1 redundancy options are used to realize a redundant optical link to a dedicated main link.

■ Available for DC, 950...2150 MHz, in 50 Ohm with SMA (f) or in 75 Ohm with F (f) connectors

■ Up to 4 times with single link modules and up to 8 times with twin modules for Rx redundancies

■ Up to 6 times with single link or twin modules for Tx redundancies

■ A mix with stand-alone optical Tx or Rx modules is allowed

■ A mix with n+1 redundancy options and mix of single link and twin modules is not allowed

■ Link gain will be decreased by ~5 dB

	Value	Condition
Return Loss	>14 dB	
Slot Requirements (including Tx/Rx Modules)	<ul style="list-style-type: none"> • 3 Slots for a single 1+1 Redundancy with Single Link Modules • 5 Slots for two 1+1 Redundancies with Single Link Modules • 3 Slots for two 1+1 Redundancies with Twin Modules 	

N+1 Redundancy Options

N+1 redundancy options are used to provide a redundant optical link to a number of main links.		
■ Available for 47...1006 MHz or for DC, 950...2150 MHz in 75 Ohm with F (f) connectors		
■ Available for DC, 950...2150 MHz in 50 Ohm with SMA (f) connectors		
■ Up to 2 times with single link or twin modules for a 4+1 redundancy option		
■ A mix of Tx or Rx redundancies is not allowed		
■ A mix with stand-alone optical Tx or Rx modules is allowed		
■ A mix with 1+1 redundancy options is not allowed		
■ Redundancy path Gain Compensation) (RGC) to align the gain of the redundant link with the related main link in case of redundancy switching		
■ Link gain will be decreased by ~2 dB for main links		
	Value	Condition
Number of Main Channels (n) per Redundancy Option	4	
Return Loss (Signal Path)	>14 dB	
Slot Requirements (including Tx/Rx Modules)	5 Slots	

Order Information

Optribution® Chassis

DEV 7134	Smart Intelligent Optribution® Chassis; 12 Slots
Option 28	Automatic Switch Back
Option 55	Change Ethernet to optical Ethernet Interface; 30 km
Option 56	Change Ethernet to optical Ethernet Interface; 1530 nm; 100 km
Option 57	Change Ethernet to optical Ethernet Interface; 1550 nm; 100 km
Option 78	Additional Web License 3-4 RU

Cabling Options

Option 40	Cabling for 1 Slot; DC...3000 MHz; 50 Ohm, SMA (f)
Option 41	Cabling for 1 Slot; 10...1006 MHz; 75 Ohm, F (f)
Option 42	Cabling for 1 Slot; DC, 700...2300 MHz; 75 Ohm, F (f)

1+1 Redundancy Options

Option 45/50/Rx	1+1 Rx Redundancy Kit; DC, 950...2150 MHz; 50 Ohm, SMA (f)
Option 45/50/Tx	1+1 Tx Redundancy Kit; DC, 950...2150 MHz; 50 Ohm, SMA (f)
Option 45/75/Rx	1+1 Rx Redundancy Kit; DC, 950...2150 MHz; 75 Ohm, F (f)
Option 45/75/Tx	1+1 Tx Redundancy Kit; DC, 950...2150 MHz; 75 Ohm, F (f)

N+1 Redundancy Options

Option 46/75/4+1	4+1 Redundancy Kit; 47...1006 MHz; 75 Ohm, F (f)
Option 47/50/4+1	4+1 Redundancy Kit; DC, 950...2150 MHz; 50 Ohm, SMA (f)
Option 47/75/4+1	4+1 Redundancy Kit; DC, 950...2150 MHz; 75 Ohm, F (f)

Contact

DEV Systemtechnik GmbH
 Grüner Weg 4A
 61169 Friedberg
 GERMANY
 Phone: +49 6031 6975 100
 Fax: +49 6031 6975 114
 info@dev-systemtechnik.com
 www.dev-systemtechnik.com

Rev. 24-Aug-2017

Technical specifications are subject to change