

DCP 2150
DCP21501FK000
DC Block/Power Inserter

General Description:

The **DCP21501FK000** is designed to permit independent Power Supply Operation for LNAs, Up/Downconverters, and Line Amplifiers by providing a method for breaking the DC continuity and re-inserting DC power. The DC Power Supply is included for the utmost in installation convenience.

Specifications:

Frequency:	270-2150 MHz
Insertion Loss:	1.0 dB \pm 1.0 dB
Frequency Response:	1.0 dB
Return Loss:	14 dB
Input Voltage	100-240 VAC @ 50-60 Hz
Voltage Output:	18 V $\overline{\text{---}}$ @ 1 Amp
RF Connectors:	Type F, 75 Ω
DC Connectors:	Terminal block
Mechanical:	3.25" H x 3.25" W x 1.25" D
Weight:	2.0lb gross (boxed) 1.6lbs net
Certifications:	CE

